




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H04B 1/713, H04J 13/06	A1	(11) International Publication Number: WO 96/10300 (43) International Publication Date: 4 April 1996 (04.04.96)
(21) International Application Number: PCT/US95/12150 (22) International Filing Date: 22 September 1995 (22.09.95) (30) Priority Data: 08/311,774 23 September 1994 (23.09.94) US (71)(72) Applicant and Inventor: SANDERFORD, Hugh, Britton, Jr. [US/US]; Sanconix, Inc., Suite 202, 101 W. Robert E. Lee Boulevard, New Orleans, LA 70124 (US). (74) Agent: REGARD, Joseph, T.; Pres. Joseph T. Regard, Ltd. (plc), Suite 100, 3200 Ridgelake Avenue, Metairie, LA 70002 (US).		(81) Designated States: AU, CA, JP, US, European patent (AT, BE, CH, DE, DK, ES, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE). Published <i>With international search report.</i> <i>Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.</i>

(54) Title: **ENHANCED FREQUENCY AGILE RADIO**

(57) Abstract

A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on a plurality of pseudo-random frequencies, comprising the steps of: scanning an available radio spectrum (517, 518); measuring (515) in a portion of the available radio spectrum, at least one of signal strength and quieting and signal lock quality, as a measurement, from an output of said frequency-agile receiver; identifying the portion of the available radio spectrum failing to provide a properly coded reception (508); generating (501) using the measurement and other system cues, a prediction of a level of undesired signal energy, within the portion of the available radio spectrum, present in a future scan of said frequency-agile receiver; and storing (505) the prediction of the level of undesired signal energy in memory location associated with the portion of the available radio spectrum.



FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AT	Austria	GB	United Kingdom	MR	Mauritania
AU	Australia	GE	Georgia	MW	Malawi
BB	Barbados	GN	Guinea	NE	Niger
BE	Belgium	GR	Greece	NL	Netherlands
BF	Burkina Faso	HU	Hungary	NO	Norway
BG	Bulgaria	IE	Ireland	NZ	New Zealand
BJ	Benin	IT	Italy	PL	Poland
BR	Brazil	JP	Japan	PT	Portugal
BY	Belarus	KE	Kenya	RO	Romania
CA	Canada	KG	Kyrgyzstan	RU	Russian Federation
CF	Central African Republic	KP	Democratic People's Republic of Korea	SD	Sudan
CG	Congo	KR	Republic of Korea	SE	Sweden
CH	Switzerland	KZ	Kazakhstan	SI	Slovenia
CI	Côte d'Ivoire	LI	Liechtenstein	SK	Slovakia
CM	Cameroon	LK	Sri Lanka	SN	Senegal
CN	China	LU	Luxembourg	TD	Chad
CS	Czechoslovakia	LV	Larvia	TG	Togo
CZ	Czech Republic	MC	Monaco	TJ	Tajikistan
DE	Germany	MD	Republic of Moldova	TT	Trinidad and Tobago
DK	Denmark	MG	Madagascar	UA	Ukraine
ES	Spain	ML	Mali	US	United States of America
FI	Finland	MN	Mongolia	UZ	Uzbekistan
FR	France			VN	Viet Nam
GA	Gabon				

Title: Enhanced Frequency Agile Radio

5

BACKGROUND OF THE INVENTION

This invention relates to robust methods of frequency re-use and frequency sharing which prevent independent radio systems from co-interference due to frequency crowding of available radio bands, and, more particularly, this invention relates to a method of frequency agility which can provide a low cost solution to many burst mode and continuous data communications applications, including security systems, fire systems, access control, energy management, remote control of model planes, remote process control, traffic light control, remote power meter reading, voice communication, radio location, or local area networks.

DESCRIPTION OF THE RELEVANT ART

The use of spread spectrum communications and techniques for diverse commercial and civilian applications has increased in recent years. By utilizing such techniques to minimize mutual interference and to provide anti-jamming advantages to multiple-access communications, as well as aiding in extremely accurate position location using satellites in synchronous and asynchronous orbits, spread spectrum techniques are known to offer the advantage of improved reliability of transmission in frequency-selective fading and multipath environments.

U.S. Pat. No. 4,799,062 to Sanderford, Jr. et al. teaches that multipath in urban areas poses a problem for accurate position location, which may be overcome by using a method of synchronization of transmissions and unique identification codes to derive relative ranging times for determining position. Compensation for multipath may include spread spectrum techniques.

U.S. Pat. No. 4,977,577 to Arthur et al. has a wireless alarm system using spread spectrum transmitters and fast frequency shift keying for achieving a coarse lock and a fine lock to the spread spectrum signal. By using spread spectrum techniques, such wireless alarm systems are highly reliable and provide a safety margin against jamming and undesirable interference. Other applications of spread spectrum techniques to commercial uses promise similar advantages in reliability in communications.

Methods for the serial search and acquisition of utilized spread spectrum frequencies are well known in the prior art, as shown in M.

K. Simon et al., Spread Spectrum Communications, vol. 3, pp. 208-279, Rockville, Md.: Computer Science Press, 1985. In addition, M. K. Simon et al., supra. at pp. 346-407 teach spread spectrum multiple access techniques such as utilizing ALOHA random access schemes.

5

OBJECTS OF THE INVENTION

A general object of the invention is to achieve superior jamming resistance compared to other spread spectrum means.

Another object of the invention is to allow multiple systems to co-exist without undesirable co-interference.

10

Another object of the invention is to minimize the effects of data collisions when a system supports numerous non-synchronized ALOHA protocol transmitters.

15

An additional object of the invention is to operate within the radio band allowed by the FCC with minimal cost and minimal frequency setting components.

A further object of the invention is to provide techniques suitable for a high level of monolithic circuit integration.

SUMMARY OF THE INVENTION

20

According to the present invention, as embodied and broadly described herein, a frequency agile method is provided which has a low cost solution to many burst mode and continuous data communications applications, including security systems, fire systems, access control, energy management, remote control of model planes, remote process control, traffic light control, remote power meter reading, voice communication, radio location, or local area networks.

25

In remote monitoring applications, the frequency agile radio system typically includes one or more centrally located data collection receivers with one or more remotely located transmitters. In control applications, one or more centrally located transmitters may communicate with a plurality of remotely located receivers. Further, the system can provide two-way polled type communications where each data node requires both a receiver and a transmitter.

30

The method for providing frequency agility includes using a frequency-agile transmitter and a frequency-agile radio system for sending a message-data signal by selecting a single pseudo-random

35

frequency on which to transmit, by generating a preamble signal on a single carrier frequency for modulating message-data, by transmitting the preamble signal for a pre-set preamble time for allowing an appropriate frequency-agile receiver to lock-on the preamble signal, and by modulating the preamble signal with the message-data signal to produce a modulated signal. The message-data signal is defined herein to be a signal having message-data.

In addition, the method for providing frequency agility includes using a frequency-agile receiver in the frequency-agile radio system for avoiding occupied radio-frequency channels in a radio spectrum by scanning the radio spectrum, identifying occupied portions of the radio spectrum, updating information identifying the occupied portions, storing the updated information in memory means, associating a time-out period with the stored occupied portions, and skipping over the occupied portions of the radio spectrum during the time-out period in response to the information and while receiving with the frequency-agile receiver.

Additional objects and advantages of the invention are set forth in part in the description which follows, and in part are obvious from the description, or may be learned by practice of the invention. The objects and advantages of the invention also may be realized and attained by means of the instrumentalities and combinations particularly pointed out in the appended claims.

BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are incorporated in and constitute a part of the specification, illustrate preferred embodiments of the invention, and together with the description serve to explain the principles of the invention.

FIG. 1 shows a configuration for a frequency agile transmitter/receiver system;

FIG. 2A and 2B is a block diagram of a frequency agile transmitter;

FIG. 3 is a block diagram of a frequency agile receiver;

FIGS. 4A-4C shows the frequency sweep over the available spectrum by a receiver to identify noise, interference or data;

FIG. 5 shows a shunt table;

FIG. 6 illustrates a frequency scan algorithm; and

FIG. 7A-7B illustrate algorithms for a trip handler and a time base shunt decay, respectively.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Reference will now be made in detail to the present preferred
5 embodiments of the invention, examples of which are illustrated in the
 accompanying drawings, wherein like reference numerals indicate like
 elements throughout the several views.

 In the exemplary arrangement shown in FIG. 1, the
 frequency-agile transmitter is designed to send one full message-data
10 signal on one single carrier frequency, with the carrier frequency
 pseudo-randomly selected. To avoid loss of data throughput, in case the
 selected frequency is jammed, the frequency-agile transmitter, after
 delaying for a pseudo-random time interval, selects a new pseudo-random
 frequency as a next frequency, which is widely separated from the
15 previous frequency, and re-transmits the entire message-data signal on
 that frequency.

 The number of redundant re-transmissions and a preselected
 average time interval between re-transmissions is programmable, which
 allows optimization to a particular installation. For example, if the
20 number of transmissions required to overcome other sources of data
 loss, such as ALOHA collisions, bit error rate, impulse noise, etc., were
 5, then by doubling the redundant transmissions to 10 would allow
 continued system operation if as much as 1/2 of the available radio band
 were jammed.

25 That is an extreme example, but consider in that example the
 time overhead, two to one, compared to the bandwidth overhead, ten to
 one or 200 to one, required by conventional spread spectrum techniques
 which use all of available radio spectrum simultaneously. The present
 invention is much more frequency efficient for equivalent anti-jam
30 performance. Further, the extra time required to re-transmit with
 even 100% redundancy can be overcome by doubling the data rate
 which causes only a 3 dB penalty in receiver sensitivity.

 The compensating advantage is large for anti-jamming and
 frequency re-use. For example, consider two adjacent but independent
35 frequency-agile radio systems, a first system A and a second system B,
 each with single frequency-agile receiver and multiple transmitters. In a

direct sequence system or a fast frequency hopper, each bit of a message-data signal is represented on every available frequency. For example, if a transmitter of the first system A were ON, and were set to use 63 frequencies, then the data messages signals received by the second system B are subjected to the multiple access suppression available, which is 18 dB or less. The frequency-agile radio system of the present invention responds differently.

If a transmitter of the first system A were ON, and were set to use 63 hopping channels, then a data message signal received by the second system B intended for second system B's own transmitter(s) has only a 1 in 63 temporal chance for being interfered. Since the receiver is actually occupying only one frequency at a time, a very small increase to data message signal re-transmissions overcomes the 1 in 63 failure rate due to collisions from the first system A.

An additional method is used to enhance resistance to wide bandwidth jamming and to selective radio channel fading. A hop list or hop algorithm is designed to provide a minimum hop distance of 500 kHz or more per frequency step, so that, if the coherence bandwidth of the radio channel is 2 MHz, then several steps overcome the fade.

Each data transmission is preceded by a pre-determined carrier preamble signal with a pre-set preamble period which provides the time needed by the receiver to sweep the entire radio spectrum available for the system to use and to lock-on to the preamble signal. Such a sweep can take from one to three milliseconds, depending on system parameters. Additionally, the preamble signal can be modulated with a repetitive data code, called a PREAMBLE SYSTEM CODE, that identifies the transmitter as belonging to a particular system, so that, if an associated receiver locks on an energy source as the receiver sweeps, the receiver can rapidly demodulate the PREAMBLE SYSTEM CODE to determine if the energy source or data packet were intended for that receiver. If not, the receiver can continue to sweep its available spectrum to search for valid incoming messages. The goal is to minimize the dwell time on any piece of impulse noise, jammer, or data packets which are intended for an unrelated system receiver.

Prior to system operation the frequency-agile receiver performs a sweep of the radio spectrum available for system operation. The receiver logs all channels with higher than expected received energy levels.

Either signal strength or a quieting detector or a phased-locked-loop "lock detect" circuit or the like is capable of supplying that information. Each usable frequency channel is associated with its own unique position in a memory device. The status of that channel is also associated with that memory location. The status information includes: 1) if the channel is "clear" or "jammed"; and 2) how many time counts must elapse prior to re-sampling to determine if that channel has become "clear".

The jammed/clear indication can also be equipped with an additional associated counter such that more than one occurrence of channel jamming is required to set the JAMMED flag. That feature makes the system more robust against impulse noise. Further, the receiver does not consider a PREAMBLE SYSTEM CODE of an unrelated system to be JAMMING.

Such occasional receptions are expected and quickly discarded prior to message "data" demodulation. Sufficient extra time is built into the preamble signal to allow for several collisions with unrelated PREAMBLE SYSTEM CODES, and for successful decode of a data message signal.

Upon initial set-up, the receiver determines the frequencies to avoid and a table containing information of such frequencies is stored in the receiver's memory. The table is then transferred via electrical means to the other associated transmitters or transceivers. The receiver can determine which PREAMBLE SYSTEM CODES are unused and available during power-up and initialization. The receiver can transfer the information on unused and available PREAMBLE SYSTEM CODES as a list of frequencies on which to transmit to other system transmitters as well.

Such information transference can be magnetic, electrical, optical, acoustic, or via a display and entered through a keypad connected to the transmitter. Once the list is so loaded, the transmitter will not transmit on the frequencies marked as 'jammed' and will use only the PREAMBLE SYSTEM CODE assigned. The PREAMBLE SYSTEM CODE can be data modulated via any appropriate means including frequency-shift-keying (FSK), binary-phase-shift-keying (BPSK), or amplitude-shift-keying (ASK) modulation. ASK modulation is less desirable, however, because ASK modulation requires time spent without full carrier presence.

One separate method no accomplish co-existence with adjacent

systems requires that both the frequency-agile transmitter and the frequency-agile receiver be highly frequency stable. Such stability must be greater than the sum of transmitter and receiver frequency uncertainty, frequency drift, and data bandwidth. For example, the

5 frequency-agile transmitter can transmit on any one of 50 frequencies, each separated by 500 kHz. If the required data bandwidth were 25 kHz, then 10-20 separate channels could fit in each 500 kHz hop slot. Therefore, 10-20 co-located systems could co-exist with no

10 co-interference, and TDMA would not be needed. To attain frequency stabilization, the frequency-agile transmitter and frequency-agile receiver would simply offset their normal hop by a pre-determined number of 25 kHz slots. Each system could determine which slot is unused and then assign each unused slot to all associated system elements. This method of transmitting on any one of 50 frequencies does

15 not work, however, if the accuracy or drift of the carrier frequency were greater than +13.5 kHz. At 915 MHz, the drift equals 15 ppm. Absent such accuracy, adjacent channels may cause interference. Therefore, the offsetting of the carrier frequency of each frequency-agile transmitter by at least the required data bandwidth plus

20 compensation for frequency inaccuracies allows multiple systems to co-exist, which utilize this technique.

Previous attempts in the prior art to integrate voltage-controlled-oscillator (VCO) components with divider and phase comparison analog and digital circuits have failed, since the phase noise

25 generated by the digital divider was induced into the VCO and phase comparator, but such phase noise ultimately reduces the sensitivity of the receiver. The preferred embodiment runs the digital divider for a brief period prior to transmission. The divided down signal is then used to produce a constant frequency error offset term to the VCO.

30 The digital divider is then disabled after the frequency error offset is measured so that the VCO can run open-loop without being subjected to phase noise of the divider harmonics. The receiver is able to compensate for any short term frequency drift during transmission.

FIG. 1 depicts a frequency-agile receiver 101 which can be used to

35 accept transmissions from a plurality of frequency-agile transmitters 103. The frequency-agile transmitters are non-synchronized and must depend on ALOHA type communicating redundancy to ensure data

receptions. Additional optional frequency-agile receivers 102 may be included to expand system coverage or add spacial diversity to reduce fading.

FIG. 1 depicts a frequency-agile transmitter 104 sending
5 message-data signals or command signals to a plurality of frequency-agile receivers 105. Each frequency-agile receiver is equipped with a unique address by which to accept commands and data intended for that unit. Once again, transmitter data redundancy is required to ensure reliability.

FIG. 1 depicts a system whereby a frequency-agile transceiver 106
10 may be linked to a single remote transceiver or by a plurality of remote transceivers 107. In such a system, each system element is associated with a unique address or identification number.

Any number of appropriate two way communications protocols may be utilized on such a system including poll-response, reservation
15 request, report by exception, etc.

As illustratively shown in FIGs. 2A and 2B, processor means, which may be embodied as a microprocessor or custom digital integrated circuit, is used to generate all transmitter timing. In order to initiate a transmission, the microprocessor 201 first selects the pseudo-random
20 frequency to be used, either by table look-up or by an algorithm. Once chosen, the microprocessor 201 selects the appropriate digital-to-analog hop setting and outputs the hop setting to the digital-to-analog 203. The digital-to-analog converter 203 in turn sets a new voltage level onto the voltage input 218 of the voltage control oscillator (VCO) 207. The microprocessor 201 then enables 213 the VCO
25 207.

The VCO 207 then begins to oscillate at the frequency selected by the voltage control input and the frequency setting resonant element 208. The frequency setting element can be any appropriate resonant or phase
30 delay device(s). The quality factor Q and temperature stability of the resonant element must be great enough to prevent drift outside of allowed FCC bands. The maximum drift and frequency uncertainty must be determined. Then a "guard band" for larger than the maximum uncertainty must be provided on both sides of the intended
35 transmitted bandwidth so that inaccuracies in the frequency setting elements do not cause transmissions in disallowed frequency bands.

If the frequency setting element 208 were not stable enough to meet

these FCC requirements with a reasonably small "guard band", then an optional divider 209 can be used to lower the carrier frequency to rates which can be digitally inputted and counted by the microprocessor 201 to determine the frequency of VCO operation. The microprocessor 201 can then generate a frequency error offsetting term to the digital-to-analog converter 203 to generate an offsetting voltage. A voltage input of the VCO 207 receives the offsetting voltage so that the VCO 207 is then adjusted by the offsetting voltage to within a required tolerance range.

This method has the advantage of not having to run closed-loop, nor be highly accurate, since this method only needs to achieve the "guard band" requirements so that inaccuracies in the frequency setting elements do not cause transmissions in disallowed frequency bands. Further, if the VCO 207 drifts during the brief message, then the receiver can track and compensate for the drift after the receiver initially attains a lock on a transmitter.

Once on frequency, the microprocessor 201 enables subsequent or final radio frequency amplifiers, embodied as the radio frequency (RF) output 212, which in turn generates a signal on the antenna 213. The microprocessor 201 then modulates the carrier frequency with the PREAMBLE SYSTEM CODE, which can be a repetitive five bit code which contains part of the transmitter's unique larger system code, or identifier code which is sent during the data portion of the transmission. The modulation of data can be FSK via resistor R2 206 or BPSK 210 or ASK 212, or any other appropriate modulation means.

The transmitted preamble 214 is sufficiently long enough for the receiver to a) search the entire radio band available, b) lock-on the transmitter carrier, and c) validate the PREAMBLE SYSTEM CODE 217. Further, preamble time is provided so that unrelated PREAMBLE SYSTEM CODES or impulse noise can be analyzed and rejected with enough time reserved to recognize and intended PREAMBLE SYSTEM CODE. Once the preamble is complete, the transmitter then sends its Message-data signal 215 via one of the above data modulation means. The message-data signal is then followed by a cyclic-redundancy-check (CRC) 216 error correction/detection code to ensure data integrity by detecting and correcting error bits appended to the message-data.

If the frequency setting process were highly stable, then the four least-significant bits of the digital-to-analog converter 204 can be

used for channel selection, providing for system co-existence on a non-interfering basis. These adjacent channels can be thought of as the last three or four significant bits of the digital-to-analog input to the VCO 207. The most-significant-bits are controlled by a pseudo-random
5 "hop frequency" generator. The least-significant bits stay fixed and cause a permanent but small frequency offset in the VCO 207. Providing both the receiver and transmitter use the same offset, the two are able to communicate. A system with a different offset is suppressed by the frequency selectivity of the receiver and ignored.

10 This hopping technique can be readily made hybrid by additionally modulating the VCO 207 carrier with other direct sequence methods.

Referring to FIG. 3, a 915 MHz modulated carrier is introduced into antenna port 300 then filtered and amplified by section 302. If
15 spatial diversity is desired, an optional section 301 can be added and controlled by generally known means to lower occurrences of selective fading.

Mixer 303 receives a local oscillator signal which is generated by a voltage controlled oscillator (VCO) 304. The frequency of the VCO 304
20 is set by a frequency setting element 305 and by the voltage preset on the voltage control input, VIN 315. The voltage control input VIN 316 voltage is generated by a digital-to-analog converter 309 or by any other appropriate linear means which can produce a controllable voltage ramp.

25 If the frequency setting element 305 has a poor absolute accuracy, or time, or temperature drift, an optional divider 308 can be used for correcting frequency error. The divided down result is compared to the crystal 315 of the microprocessor 314 which then produces a frequency error offsetting voltage via the digital-to-analog
30 circuit 309.

The down converted output of the mixer 303 can be immediately demodulated or passed first through an optional second conversion state 306.

In the preferred embodiment, prior to data demodulation, the
35 signal is first band-limited by a fixed frequency and bandwidth filter 307. The signal is then decoded by the data demodulator. The demodulator means 316 or 310 must match the transmitter's data modulation utilized.

In the preferred embodiment, a phase lock-loop (PLL) 310 is used to detect FSK modulated data. The available frequency spectrum is initially swept through and monitored via a wider PLL loop intermediate frequency bandwidth selected by wide/narrow bandwidth select 311, so
5 that the entire available bandwidth can more quickly swept through. The energy detector, carrier lock-detect, quieting detector or equivalent means must have a very rapid response time, which should exceed the impulse response time of the filter 307 that is, $1/110 \text{ kHz} = 9 \text{ microseconds}$, in this example.

10 Once the carrier is initially detected, a more narrow bandwidth can be selected by 311 which is more representative of the data bandwidth required for the elected data rate. This narrowing of the bandwidth improves the carrier to noise ratio. The microprocessor 314 or other linear means then can be used to close the frequency control loop and
15 track and compensate for further transmitter or receiver drift components.

If the drift components are minimal, and the transmitted message brief, a frequency control loop will not be needed. At this point, data can be demodulated. Alternatively, if the PREAMBLE SYSTEM CODE or some form of transmitter identifier, does not match, noise and interference
20 in occupied portions of the radio spectrum can be identified and skipped over while the transmitter transmits.

If the transmitter is hybrid modulated with other spread spectrum modulation, such as direct sequence, then direct sequence demodulation must also be added after the hopping frequency is locked
25 on. This would be an opportunity to include in the combination a simple parallel correlator means to decode data. Such a combination would be well suited to time-of-flight radio location applications. The hop sequence would be optimized for anti-jam and the parallel correlator optimized to "time stamp" the incoming message.

30 As an alternative to controlling the voltage input of a voltage controlled oscillator 304, a numerically controlled oscillator or a frequency synthesizer may be used, or any method as is known in the art which can select a frequency based on a control input. If AGC blanking is employed by 'turning off' the front-end of the receiver, then the rise and fall times
35 of the amplifier 302 and/or circuit 301 can be controlled in order to reduce unwanted bandwidth expansion from the effective amplitude modulation resulting from the rapid blanking control signal. Alternately, the narrowest

IF, or baseband, filter can be dumped during the AGC transition time.

As an alternative to the D/A converter 309, dedicated hardware can be implemented which provides a monotonic increasing or decreasing ramp or saw tooth waveform. Such implementations are well known in the art and can be fashioned from operational amplifier integrators.

The frequency agile receiver voltage controlled oscillator 304 also may be designed such that the narrowest IF filter is not the last one in the receiver's IF line up. It is further possible to use the voltage controlled oscillator 304, or an equivalent, to sweep a second local oscillator or any other intermediate frequency conversion stage in the receiver's IF line-up.

The "wide/narrow bandwidth select" signal 311 could alternatively be used to select a "chirp/conventional" type filter. The phase-locked-loop circuit 310 could be replaced with any of the IF/baseband filter approaches described herein. The D/A converter 309 could additionally provide the AGC control signal with appropriate sample and hold circuits, or an additional D/A converter could be provided for that purpose.

FIGS. 4A-4C illustratively shows the frequency sweep operation of the present invention. In normal operation, the receiver sweeps over the available spectrum to identify cases of noise, interference or data, and to store such identified portions of the spectrum in a jammed channel list.

When no data and no new interference since the last memory update of the jammed channel list is detected during an associated time-out period and after a plurality of failed attempts to detect new data or interference have occurred, the VIN 316 input appears as depicted by FIG. 4A. The VIN will linearly sweep 401 until the microprocessor 314 determines, via the microprocessor's list stored in memory, a frequency to skip over 402 while the receiver is receiving. Once the maximum frequency point is reached, the VIN 315 input reverses the direction of sweep 403, in order to minimize the required impulse response of the VCO 304.

If new impulse noise or jamming were detected 404, such noise or jamming causes the CPU's 314 algorithm to temporarily stay on that frequency. The algorithm then attempts to decode a 5 bit PREAMBLE SYSTEM CODE. If that were not possible, then the VIN 316 sweep resumes its normal path. The PREAMBLE SYSTEM CODE can also be Grey coded or Manchester encoded so that impulse noise could be more

rapidly detected as an illegal sub-sequence without having to monitor all 5 bits.

If the PREAMBLE SYSTEM CODE 217 matches, then the VIN stays constant 405 or in-track with a drifting input frequency 300 if a frequency locked loop (FLL) is used, so that transmitter and receiver frequency drift is compensated. The processor 314 then attempts to decode a data message 215 and CRC 216. After completion of the message decode, the normal search algorithm resumes and the previous path of VIN 316 continues.

Performance can be further enhanced by not skipping over the occupied portion or portions of the band, but rather by dynamically predicting future noise and jamming signal strengths and then only attempting to decode future signals which are higher than those predicted levels. If a future desired signal were lower in power than a jamming level, then the signal-to-noise ratio is too low for the data to be decoded and, therefore, the frequency agile receiver should avoid dwelling on those frequency bins. If, on the other hand, a future desired signal were higher in power than a jammer or a background noise level, and were higher by an amount at least equal to the carrier to noise ratio required to decode data at an acceptable bit error rate (BER), then the frequency agile receiver should dwell on that frequency and attempt to decode a PREAMBLE SYSTEM CODE and/or voice or data.

The frequency agile receiver seeks to eliminate dwells on frequency bins which contain unrecoverable messages. The frequency-agile receiver should not waste time during the scanning portion of the algorithm, as such waste may prevent the receiver from finding an otherwise recoverable desired signal residing in an unoccupied portion of the spectrum later in the frequency sweep. Therefore, if the frequency agile receiver had a 'perfect' prediction of the background noise, jamming and interference contained within the frequency band in use, then the frequency agile receiver algorithm would be able to optimally either dwell on a new signal which exceeded that prediction, or minimize wasted dwell time and continue the sweep into other potentially useable areas of the spectrum. The goal of this technique is therefore accurate prediction. The receiver's algorithm should seek to use information gathered both in the current frequency sweep, as well as information collected from previous frequency sweeps, to make the best prediction of what the background noise, jamming and

interference environment will look like in the next successive frequency sweep, which may be only one or several milliseconds in the future.

If the types of interferers could be identified, then prediction could be made easier or more accurate. There is a wide breadth of potential jamming and interfering sources which may appear in the unlicensed portions of the radio spectrum which are attractive for operation due to FCC regulatory considerations. The types of jammers which may appear in these bands include on/off keyed devices, and fast and slow frequency hopping devices, including data sets and portable telephones. Portable phones include those which find an initially unoccupied frequency and remain on it for the duration of a conversation, as well as those which are continuously frequency-hopped according to the FCC's definition. Such frequency hopping devices are likely to dwell on any single frequency in the range of 1 ms to 400 ms.

Other potential jammers include direct sequence devices operating at either low or high baud rates. The low baud rate devices typically occupy 1-3 MHz of bandwidth with dense spectral line spacing. The high baud rate devices require high chipping rates in order to achieve the required FCC process gain. If the data is not being richly modulated, these high chip rates lead to sparsely spaced spectral line peaks. Depending on data modulation type, such high chip rates can lead to sparsely populated peaks filled in by energy valleys over the entire spectrum used, which is likely to be 20-60 MHz.

Amateur video transmission may also be found in these bands, as well as continuous wave (CW), continuous transmitting jammers such as pilot tones, or unintentional harmonics caused by lower frequency licensed or unlicensed devices or FCC Part 15.249 devices. Fast fading effects from mobile user transmissions and slow fading effects, such as those experienced in a building at night, will also need to be considered. Taken as a whole, there are wide areas of bandwidth which are either unused, of low intensity, or which are unused during those periods in between burst type transmissions.

The instant invention can also be used in a two-way transceiving system. Such a system takes advantage of dynamic reallocation of hop channels, providing that the number of hop channels exceeds that number required by the FCC's regulations. For example, a receiving device can transmit a map of its background noise, jamming and interference

environment to a distant transceiver such that the transmitter associated with that distant transceiver can reallocate transmitting frequencies to concentrate on those frequencies of the receiver that are least occupied.

5 These considerations taken, the frequency agile receiver can use an algorithm which sweeps in a linearly increasing frequency and then resets to an initial frequency, sweeps in a linearly decreasing frequency and then resets to the initial value, sweeps in a ramp-up/ramp-down fashion, or searches over a pseudo random order of the available frequency bins. A frequency 'bin' is set by the most narrow intermediate frequency (IF) or
10 baseband filter, or a portion thereof, which is being analyzed by the receiver in one unit time. In addition, the receiver can skip over portions of the band which are too densely occupied to be of value and seek to extract useable information from two separate portions of the available band, which may be removed in frequency from one another by many
15 megahertz.

In a preferred embodiment of the instant invention based upon prediction, a present measured signal strength or quieting or signal lock quality reading from an individual frequency bin is compared to the last
20 best prediction of the noise, jamming and interference in that bin. The receiver does not dwell on that particular frequency bin unless the presently measured signal strength or quieting or signal lock quality reading is higher than the predicted environment level by an amount roughly equal to the carrier-to-noise ratio required to decode a valid message. Once this threshold is met, the receiver will 'TRIP' and dwell on
25 that channel for the amount of time necessary to determine if valid data can be extracted from that frequency bin.

The algorithm then falls into three modes: NORMAL MODE, TRIP MODE and RECOVERY MODE. In NORMAL MODE, the radio spectrum is scanned and radio energy received from background noise and from manmade jamming
30 sources which is at approximately static power output is processed. Small variations in received power do not exceed the dynamic tracking available in the frequency agile receiver's algorithm and therefore do not cause an entry into the TRIP MODE, i.e., associated fading changes of known jammers are either sufficiently small or slow so that the modulation form on the
35 jammer will either have slow variations in time or small variations in signal power. The goal during these occurrences of slowly varying signals in NORMAL MODE is for the frequency agile receiver algorithm to apply

averaging to these sources of radio energy which, in fact, tend to average to a roughly static level.

The next mode of the frequency agile receiver's algorithm, TRIP MODE, is triggered when a signal exceeds the predicted level plus the required carrier to noise ratio, signaling the potential for decoding a valid message. The receiver's algorithm enters the TRIP MODE when subjected to rapidly changing background noise or a manmade jamming source which is impulsive in nature, from other hoppers either fast or slow, from a new transmitting source which has just been turned on, from fast constructive fading from an existing transmission, from a larger modulation variation of a transmitter which has already been on, or as the result of multi-tone IMD products in receiver. The last source of a TRIP is that of a VALID signal.

A VALID signal may contain a correct PREAMBLE SYSTEM CODE, in which case useable data may be recovered. A VALID signal may also result from a PREAMBLE SYSTEM CODE from a similarly coded frequency agile transmitter but one which was not intended or desired by the receiving system. This is possible since the PREAMBLE SYSTEM CODE is used in a fashion similar to that employed with Code Division Multiple Access. A VALID but unwanted signal message would be discarded prior to data decode. In either VALID case, the receiver's algorithm typically does not seek to alter the prediction variables. Alternatively, if VALID messages from similarly coded systems are anticipated to be long in duration, the receiver's algorithm can be implemented to rapidly alter the prediction variable.

Lastly, there is RECOVERY MODE. when a jammer goes away, or is reduced in unwanted signal energy, the receiver's algorithm seeks to make that portion of the radio band available as rapidly as possible.

In view of the three modes and the different needs of each, the present invention proposes a dual algorithmic prediction approach. One portion of the algorithm attempts to apply averaging to those signals which are anticipated to remain within a relatively static range. The other portion of the algorithm tries to rapidly adjust to a signal which is likely to have large fluctuations in signal strength. This dual approach yields a type of hysteresis, such that if the signal stayed within a predetermined window, or within a dynamic TRIP LEVEL range, then the algorithm performs averaging within that window.

If the received signal fell outside of the predetermined window, or

the dynamic TRIP LEVEL range, then the receiver's algorithm seeks to rapidly match that new reading. This can be accomplished with classic hysteresis or windowing techniques. Alternatively, rate of signal change can be tracked. Rate of signal change methods which are common in the art include Type II servo loops which seek to match or anticipate second or third order, rate of change phenomenon.

It is important to provide means in the receiver's algorithm such that 'one time' events have a minimal skewing effect on the prediction algorithm. One time events can come from very rapid fading, frequency hoppers, rapid impulse noise, or large but infrequent modulation deltas. In addition, statistics can be maintained on each frequency bin measured to show the percentage of successful transmissions received, or the percentage of successful data throughput over a unit of time. Since frequency hopping transmissions will be randomized over the frequency band available, if there is no jamming present in the frequency band in use, then all of these statistical successes will be roughly equivalent. Statistics can also be maintained on the number of false TRIPS experienced in each frequency bin. The receiver can then take advantage of this information to either initially, or dynamically, reallocate the channels by either ignoring those channels exhibiting excessive false TRIPS and thereby preventing wasted dwell time, or sending information to the associated transmitting devices so that the -transmitting devices avoid utilizing those frequency bins in future transmissions. If frequency avoidance is used, the transmitter still transmits on a specified number of channels sufficient to meet FCC requirements.

A goal of the frequency agile receiver is to sweep the available band as rapidly as practicable while providing as much resolution per frequency bin as possible. A further goal is to yield an accurate representation of the radio environment, while minimizing signal strength loss. The receiver may therefore take one or more signal strength or quieting detection or signal lock quality samples per transmitted bandwidth. The receiver also sweeps as rapidly as possible in order to minimize the required transmitter preamble time and make a finer time resolution prediction. The last IF filter, or the one with the narrowest bandwidth, is the filter that is most affected by these requirements and is, therefore, the filter that sets the limit of performance.

Typically, in a conventional filter, as a signal is swept through it at,

or approaching, a time proportional to the reciprocal of bandwidth, two limiting effects occur. First, the filter loss increases, thereby reducing the effective sensitivity of the resulting receiver. Second, the energy from a previous frequency bin dwells in the filter while the next frequency bin is being analyzed. The energy dwelling from frequency bin to frequency bin is a form of ringing, and is due to the infinite response time of the filter. The dwelling energy from frequency bin to frequency bin makes measurements appear to smear into one another. Thus, the energy from a strong jammer will dwell in the filter one or more sample times delayed and can be greater than an otherwise decodeable desired signal having a weaker signal strength.

There are several ways to minimize these two effects on the performance of a rapidly sweeping frequency agile receiver. The method previously described using two different IF filter bandwidths can be beneficial. The step using a wide bandwidth filter is used initially during the sweep time. The wide bandwidth filter has a faster response time than a narrow bandwidth filter. The wide bandwidth, however, allows additional noise to be placed within the filter, thereby reducing the effective sensitivity of the receiver and equivalent process gain. Once the desired signal is acquired, a narrow bandwidth filter is used when decoding the data portion of the message. while the receiver is no longer slewing the VCO.

A method which overcomes this previous shortcoming is to use a chirp filter matched to the sweep speed of the receiver's slewing VCO. The effective bandwidth of the chirp filter can be matched to the desired incoming signal. The chirp filter reduces the effects of ringing or smearing from the filter, and at the same time achieves full receiver sensitivity. Once the initial signal is acquired during the sweep mode, the receiver stops sweeping the VCO and switches to a conventional narrowband filter matched to the data bandwidth, prior to attempting to decode data.

An alternative to using the chirp type filter during the acquisition phase is to use an IF filter with the narrowest bandwidth or baseband filter, match that filter bandwidth as closely as possible to the bandwidth of the transmitted signal, and then provide means for dumping the filter after each sample. This technique eliminates smearing due to signal energy dwelling in a filter during subsequent samples. Another approach is to use a filter designed with a finite impulse response (FIR) so that unwanted

energy cannot linger in the filter. when using the foregoing approaches, the chosen filter should have a fast response time, or signal energy will be lost in fast sweep/fast sample implementations, effectively reducing the sensitivity of the receiver.

5 A further approach is to use a digital signal processor (DSP), or the equivalent, to provide a fast Fourier transform of a section of bandwidth equalling one or more frequency bins simultaneously. A DSP can also simultaneously implement multiple narrowband filters, thereby increasing the effective sweep speed of the radio spectrum utilized. A DSP algorithm can
10 be flexible, and may implement a chirp type filter during the sweep portion of the receiver algorithm, and/or a narrow band conventional type filter once the algorithm locks to a single frequency.

Another approach is to use a single IF filter which has excellent impulse response time as well as desirable ringing/smearing characteristics.
15 Attractive results have been achieved by both gaussian and synchronous filters. The shortcoming of these filters is that the skirt roll-off degrades with high signal levels. These filters work well in combination with AGC strategies, as described below, to minimize the peak energy which may be introduced.

20 The receiver 310 may use any of several filter implementations, with the chosen filter providing desirable results, which may be enhanced by the foregoing approaches. The filter implementations include use of a phase lock loop design, a DSP filter, an appropriate surface acoustic wave (SAW) implementation, a switched capacitor bank, or any of the classic
25 active filter techniques having filters modified for dumping their energy storing elements, e.g., capacitors. In these filter implementations, the leading edge of the filter should be as sharp as practicable during the condition when the filter is being swept at a rapid rate. The benefits of the sharp leading edge include narrowing the effective bandwidth,
30 improving the co-channel performance, and improving resistance to the effects of nearby jamming signals.

Prior to anticipated higher levels of jamming, the sweep speed of the VCO can be slowed down so that the filters can settle, or the sweep speed of the VCO can be significantly increased such that very little energy is
35 collected by the narrowest IF or baseband filter.

A further alternative, which can be used with the foregoing methods, is to provide automatic gain control (AGC) at the front-end stage, or at an

intermediate frequency stage, of the receiver. The AGC can be in the form of on/off signal blanking, e.g., gain dumping, or may be in the form of smaller incremental steps operating over a wide dynamic range. If the AGC uses smaller incremental steps, then the receiver's algorithm can attempt to match the AGC signal to that of the incoming signal such that the resulting RF output of the front-end stage of the receiver yields a nearly level signal strength envelope as the local oscillator is swept. using an AGC with smaller incremental steps reduces undesirable effects from the AGC control signal, which would tend to expand the bandwidth of an incoming RE signal and could cause the equivalent of smearing. This AGC strategy can also serve to reduce the effects of front-end signal compression and of undesired intermodulation components which may be created by non-linear operation of subsequent receiver stages.

If the AGC used 'on/off' blanking, then undesirable amplitude modulation artifacts may result from a rapidly changing AGC control signal. It is therefore desirable to moderate the ramp speed of the 'on/off' control signal. Such moderation techniques are well known in the art.

The drawback with a full AGC approach is that the receiver's algorithm primarily uses time cues in order to decrease the level of predictions of future noise, jamming or interference sources. With a full AGC approach, the AGC circuits eliminate signals which have fallen below immediate predicted levels and therefore make these signals unmeasurable. A compromise approach to full AGC, is to allow a portion of the RF signal energy to be above the noise floor and therefore remain measurable. This compromise approach allows the receiver algorithm to take advantage of those measurements to more rapidly predict decreasing levels of noise, jamming and interference. The compromise approach allows most of the unwanted anticipated signal energy to be eliminated in the very first stage, or early stage, of the receiver and still provides very robust performance.

The architecture of the frequency agile receiver can be designed with a digital-to-analog converter, driving the AGC circuit with sufficient resolution so that the resulting received signal strength indication (RSSI) level is compared against a single TRIP LEVEL. With such an architecture, the resulting RSSI level, or quieting output level, does not have to be analog-to-digital converted, thus reducing the cost and complexity of the architecture.

In the typical AGC approach, the receiver's first section 301, and/or

section 302 is either blanked or replaced with a circuit capable of variable gain and/or variable attenuation. Further, the AGC or blanking circuits can be distributed in the receiver's IF strip for reducing cost and improving performance. It is, on the one hand, desirable to reduce unwanted signal power immediately at the front-end of the receiver. It also is desirable to place a variable attenuator after an IF filter or baseband filter which is as narrow as practicable, but which does not create the limiting factor of ringing or smearing. The bandwidth of the filter 307 would likewise be increased such that the impulse response time and signal loss of filter 307 would not be a factor to the following stage.

A further enhancement to the receiver's prediction capabilities is to provide an adaptive TRIP LEVEL. The adaptive TRIP threshold has several areas of value. As the receiver sweeps through the available band at increasingly rapid rates, the narrowest bandwidth RF, IF, or baseband filter will increasingly attenuate the received signal, due to response time. It is, therefore, desirable to TRIP the algorithm in the most sensitive manner possible while at the same time not creating so many false dwells that the receiver is likely to entirely miss a preamble of a valid transmission on a later frequency. This can be accomplished with the support of the software filters which seek to predict background noise, jamming, and interference. The TRIP threshold can be effective even at extremely low values, such as 3 dB.

The system of the instant invention seeks to balance sensitivity with robustness against a hostile environment. In order to be consistent with this approach, the PREAMBLE SYSTEM CODE can be designed to allow for a single bit error within its repetitive sequence and still uniquely decode the preamble's ID. This approach typically expands a 5 bit code to more than five bits. Designing this facility into the coding of the PREAMBLE SYSTEM CODE effectively provides for single bit error correction, making the PREAMBLE SYSTEM CODE more robust, while at the same time lowering the needed E_b/N_0 to successfully decode the PREAMBLE SYSTEM CODE bits. This approach is consistent with very low TRIP levels. For example, if a 5 bit PREAMBLE SYSTEM CODE were expanded to 10 bits, to allow for one bit of error tolerance, then a bit error rate as low as 1×10^{-1} would provide usable results. The E_b/N_0 required for such a low bit error rate, depending on modulation type, can be as low as 1 to 3 dB.

It is usually desirable to rapidly discard a transmitted message which

is not intended for, or desired by, the receiving device. This may be accomplished by comparing further repetitions of a PREAMBLE SYSTEM CODE in the transmitted preamble and, if a subsequent code does not match, to abort the message. Additionally, a 'full' system code in the transmitted message, representing hundreds or even millions of unique systems, can be matched against a full system code which is stored within the frequency agile receiver's memory means.

The frequency agile receiver can store a table of desired transmitter identification's (ID's) in memory means. The transmitter ID, or full system code, can be located near a 'data start' marker at the beginning of the data message. If the ID code or full system code does not match with one of the desired codes stored in the memory means, then that message can be aborted without forcing the receiver to dwell for an entire message time. The 'data start' pattern can be provided by either embedding an illegal bit sequence, such as three or four sequential 1's or 0's in a row, or the data start pattern can be a reserved orthogonal PREAMBLE SYSTEM CODE. Since the PREAMBLE SYSTEM CODE can be so robust, the following portion of the data message would benefit from an interleaved forward error correction scheme which approximates the robustness of the PREAMBLE SYSTEM CODE.

A wide range of modulation types may be used with good results in the instant invention. In general, the modulation type should use the least amount of bandwidth possible while maintaining a very rapid skirt roll-off. Desirable modulation forms include, but are not limited to, low index FSK, SFSK, FFSK, MSW, and GMSK.

A narrow bandwidth utilized at the transmitter allows for a narrower bandwidth to be used at the receiver, serving to increase sensitivity and to better reject jamming and interference. Conversely, as the bandwidth is widened to allow for increasing data modulation rates, the overall message dwell time is reduced. Brief messages are desirable to avoid the effects of a rapidly changing RF environment and of undesirable interferers such as frequency hoppers. Minimum bandwidth is desirable for co-channel isolation and to minimize the amount of undesirable signal energy which can be introduced into the narrowest IF filter or baseband filter. Specific applications of the instant invention can be evaluated to make this trade-off.

The frequency agile receiver can be applied to transmitters which do not transmit on a multiplicity of pseudo random frequencies. In such a

case, the receiver provides the benefit of automatically eliminating frequency uncertainty caused by an unknown transmitter frequency. This reduces the cost of frequency setting elements while optimizing receiver sensitivity by permitting bandwidths approximately equal to the bandwidth of transmitted voice or data. This provides an attractive approach for cordless phones and PCS applications.

FIG. 5 shows a shunt table. The shunt table is stored in memory means and is updated either during system setup and/or dynamically through ongoing system operation. The purpose of the shunt table is to associate frequency bins, relating to received frequencies, i.e., a current or voltage input of the receiver's VCO or synthesizer divider inputs, to other information concerning the past history of that frequency bin. Past history information can enhance predictions of future anticipated noise, jamming level or interference level within that frequency bin. Each frequency bin may be either approximately equal to the bandwidth of the transmitted signal or may represent a fraction of the bandwidth of the transmitted signal. It is also possible to make the frequency bin wider than the transmitted bandwidth, which can improve sweep speed but does not optimize sensitivity.

The frequency bin number 500 can be stored in the shunt table as a variable. Alternately, the frequency bin number 500 can be associated with a physical memory address in a table whereby an offset number can be used at a start 517 address to index into the table. The end 518 of the table represents 'n' entries which equal the number of hops available or practically 2-4 times the number of available hops utilized by the transmitter to provide finer spectrum resolution at the receiver. Optionally, the D/A value controlling the receiver's VCO 516 can also be stored in the shunt table. This value is the equivalent of the selected receive frequency. The advantage of storing the frequency bin number 500, or of storing the value of the D/A converter which drives the voltage input of the receiver's VCO 516, is that the receiver algorithm can then skip through a wide variety of frequencies which may not be adjacent to one another. This further helps facilitate systems which take advantage of dynamic reallocation of frequencies.

Each frequency bin is associated with a SHUNT LEVEL 501 which represents the prediction from the receiver algorithm's previous frequency sweep(s). The next piece of information, which is optional, is a single bit

which indicates that the last reading taken from that frequency bin was a false TRIP 515. This bit can be replaced or augmented by the following optional variables. Attack 502 may be stored to provide a second order representation of the rate of rise of undesired signal energy. It can be
5 used as part of a servo loop to track an increasing level of jamming energy in this frequency bin. Decay 503 provides the same functionality as attack, but is used for jamming signals which are reducing in signal energy.

Percent yield 504, which is optional, may maintain a figure of merit
10 relating to the success of the receiver algorithm in extracting usable desired messages from that frequency bin. The average false trip 519 table entry, which is optional, tracks the number of false dwells that occurred on that frequency bin which may have been caused by impulsive jammers. This information can then be used to either avoid spending receiver dwell
15 time on that bin or as a method to transfer this receiver's algorithm to TRIP and dwell on that frequency bin.

A desired signal 511 is shown which is below the SHUNT LEVEL plus TRIP LEVEL 510, and is therefore rejected as unrecoverable. Such a signal would not provide a sufficiently high carrier-to- noise ratio to reliably
20 decode a message. A desired signal 512 is shown above the SHUNT LEVEL plus TRIP LEVEL and causes a TRIP of the receiver's sweep algorithm such that the receiver dwells on that frequency bin and correctly decodes the desired signal. Alternately, both the SHUNT LEVEL and the TRIP LEVEL can be summed prior to storage in the shunt table. The hysteresis range
25 around the SHUNT LEVEL is shown as 519.

Referring to FIG. 6, the receiver software includes an algorithm to sweep or pseudorandomly step through a list of frequencies contained in the shunt table. The TRIP handler seeks to identify if the TRIP is a result of a desired message or undesired noise, jamming or interference. If the
30 TRIP was due to undesired noise, jamming or interference, the TRIP handler readjusts the SHUNT LEVEL 501 an appropriate amount.

Once the receiver software is initialized, it jumps to point 'A' 621 in order to enter the frequency sweeping algorithm. Next, if a chirp type filter architecture is optionally utilized, then the algorithm selects the chirp
35 IF or baseband filter which is architecturally prior to the hardware in the receiver which measures either signal strength, quieting or signal lock quality. Alternatively, the sweep algorithm can be re-entered through node

'B' 622 once a pass of a single frequency bin has been completed.

If the instant invention uses an implementation whereby the voltage controlled oscillator 304 runs predominantly open loop, then occasionally an additional step may be used to calibrate the voltage controlled oscillator 304 to a known reference such as a crystal 315. This is repeated in a time interval which is less than the maximum acceptable receiver frequency drift. This frequency measurement computation can be accomplished through the optional digital divider 308 in conjunction with timer counter hardware and/or software within CPU 314 or by phase locked means.

Alternately, if the voltage controlled oscillator 304 is part of a synthesizer, once settled on an initial frequency, the loop can be opened and the voltage into the voltage controlled oscillator 304 can be integrated, or ramped, by any means as is known in the art. As a further alternative, the voltage controlled oscillator 304 can sweep through an in-band 'intentional jammer' which is purposely generated by the receiver's hardware. Such an 'intentional harmonic' would also be modulated in a manner such that the receiver's algorithm could uniquely identify the harmonic.

The 'intentional harmonic' would be generated by a stable reference such as a crystal source so that it would appear at a known position in the band over which the receiver was sweeping. The algorithm within CPU 314 would then be able to use this as a known reference to correct the actual scan position of the voltage controlled oscillator 304. Additionally, more than one harmonic can be placed in-band so that a two point correction or a piecewise linear curve fit could be implemented by algorithmic means.

The frequency bin pointer 508 is incremented 601 to point to the next shunt table entry. Alternatively, the frequency bin pointer 508 can be stepped through a pseudo random sequence, or other randomizing means. Next, if step 602 decides the frequency bin pointer 508 has reached the end 518 of the table, then control of the algorithm passes to reset 603 the shunt table pointer. Next, the voltage controlled oscillator 304 is slewed 604 to the start frequency so that the voltage controlled oscillator 304 has adequate settling time prior to taking the next read. Optionally, the SHUNT LEVEL 506 is dynamically recalculated starting with a comparison of the false TRIP count 507 to the number of additional PREAMBLE SYSTEM CODE repetitions designed into the transmitted preamble 605. If the false TRIP count 507 is lower than the number of additional repetitions, then the TRIP

LEVEL 506 is reduced 606 by one half of one dB, or by some other preselected amount. If the false TRIP count 507 is not less than the number of additional repetitions, then the TRIP LEVEL 506 is increased 607 by one half of one dB, or by some other preselected amount. To prevent
5 the TRIP LEVEL 506 from increasing or decreasing into unreasonable ranges, the TRIP LEVEL is constrained 608 to a TRIP LEVEL which is greater than 3 dB but less than 10 dB. These numbers can be preselected to any desirable bounds. Alternatively, the dynamic TRIP point can be updated on every M^{th} pass. Lastly, the false TRIP count 507 is reset 609.

10 Control is then passed to reading 611 the SHUNT LEVEL from the shunt table. The step of writing 612 the SHUNT LEVEL is optional, and may be used alternatively to augment the rest of the algorithm. The SHUNT LEVEL 501 is used either in part or in whole to control the AGC input of the front-end of the receiver. The AGC input would be in block
15 301 and/or block 302. Alternatively, variable gain or variable attenuation may be distributed through any part of the receiver. The step of writing 612 the shunt level can be used to eliminate or reduce undesirable signal energy which is predicted by the shunt table. The step of writing 612, therefore, reduces the amount of energy which may cause subsequent RF
20 stages to either overload, ring or create undesirable non-linear signal components. The step of writing 612 can also be used to increase the effective dynamic range of the receiver system. A form of blanking can be implemented by simply disabling the amplifier stage in 302 and/or 301, thereby effectively reducing the input signal by approximately 30 dB. The
25 AGC control signal also may be synchronized with subsequent filter dumping to eliminate unwanted Fourier components which may be measured on the receiver's output.

Next, the algorithm increments steps, ramps or pseudo randomly jumps 613 to the next VCO frequency. This can also be accomplished by
30 reading a D/A, or frequency, value 516 from the shunt table. Next, the algorithm optionally may dump 614 the last narrowest IF or baseband filter. The algorithm then allows a delay 615 which is appropriate for the IF or baseband filter to settle. Once the filter settles, the A/D converter 313 reads 616 a level representing signal strength, quieting or signal lock
35 quality. The new reading is then compared 617 to the TRIP LEVEL 506 plus the SHUNT LEVEL 501. If the algorithm stores a value in the shunt table that is equal to the SHUNT LEVEL plus the TRIP LEVEL, then the new

reading is compared only to that combined stored level. If the new reading exceeds this level then control is passed to C 719 for TRIP handling. If this new reading is not greater, then the algorithm then seeks to find if the new reading is 618 less than or equal to the SHUNT LEVEL 501 minus the TRIP LEVEL 506. Effectively, this creates a hysteresis band which is plus or minus the TRIP LEVEL 506 selected. If the reading is within a hysteresis band then control passes to set 619 the SHUNT LEVEL in order to provide ordinary averaging of the SHUNT LEVEL to the newly read data. If the new reading is outside of the hysteresis band, then the algorithm seeks to very rapidly move the SHUNT LEVEL to the newly read input 620. Alternatively, attack 502 and decay 503 variables may be used from the SHUNT LEVEL to augment the hysteresis algorithm and provide means to create averaging about levels which tend to be static while simultaneously rapidly acquiring jamming signals which are changing quickly. Lastly, control is directed to B 622 whereby the algorithm repeats itself.

If the step of comparing 617 the new reading is used in conjunction with the AGC function of setting 612 the shunt level, then the SHUNT LEVEL 501 is reduced by an amount equal to that written into the AGC circuit. If gain stage disabling is employed, then the SHUNT LEVEL is reduced by an amount equal to the attenuation of the disabled amplifier, or amplifiers, such as the ones in block 302 and/or 301. Further, in AGC assisted implementations, the 'below shunt' hysteresis provided by the steps of comparing 618 and setting 620 will only be effective if the AGC value is only a portion of the total SHUNT LEVEL 501. Lastly, if the instant invention is implemented with AGC operating over the entire dynamic range of the receiver, and such that the receiver algorithm uses detected RSSI to seek a zero point, then the SHUNT LEVEL 501 can be reduced by time based decay means per FIG 7B.

As an alternative to the above algorithms, an implementation of the instant invention may post-process TRIPS which are initially identified as increases in signal level, but whereby the algorithm does not TRIP and dwell on those frequency bins. In such an implementation, during the sweep time, the algorithm would utilize an additional column within the shunt table to indicate that the present reading yielded an increase Over the prediction relating to the present frequency bin. After a complete pass of the available radio spectrum, the receiver's algorithm could then choose the most likely candidate to attempt to decode a PREAMBLE SYSTEM CODE,

or some transmitter identifier or data. This post-processing approach would provide additional system cues to make a decision before spending time dwelling on any individual frequency bin.

Once the algorithm in FIG. 6 is tripped, control is passed to C 719 of
5 FIG. 7. Initially, the method deselects 700 the chirp type filter, if one has been used, and selects 700 the non-chirp alternate filter. A non-chirp filter is used during data decode since the voltage controlled oscillator 304 does not slew the receiver's local oscillator once a TRIP occurs. Next, the method may optionally use feedback means, such as a quad circuit or a
10 frequency error output from a PLL, to provide 701 drift correction between the transmitting and receiving devices. A frequency error term is established and is used to compensate the voltage controlled oscillator 304 through the D/A converter 309 if the voltage controlled oscillator 304 is open loop. Alternatively, if closed loop means such as a synthesizer were
15 used, then the feedback loop can be opened and the voltage controlled oscillator 304 can be directly slewed. Alternatively, if a closed loop synthesizer were used and remained closed, a directly compensating reference crystal 315 steers the output of the voltage controlled oscillator 304. This last approach has the advantage of automatically correcting the
20 data sample clock at the same time the voltage controlled oscillator 304 frequency error is corrected. In the drift correction approaches, however, the tracking range should be governed to prevent the receiver from locking onto an adjacent, or more powerful, undesired signal.

The method seeks to decode 702 the PREAMBLE SYSTEM CODE which
25 is repeated in the transmitted signal. This code may be repeated several extra times as determined by the anticipated number of false TRIPS in the frequency sweep of FIG. 6. The PREAMBLE SYSTEM CODE can provide timing information so that the receiver can clock data at an optimal sample point. The PREAMBLE SYSTEM CODE may be a 5-10 bit code designed with
30 special characteristics providing cues to the frequency agile receiver so the frequency agile receiver can rapidly abort attempts to decode undesired radio energy as a message. One such characteristic cue can be detected 703 in three or four bit times, such as an illegal bit sequence and, if not found, the handler aborts to step 710. Additionally, the receiver
35 hardware or software algorithms may be able to provide information indicating that the modulation itself is not appropriate or recoverable, in which case the TRIP handler aborts to step 710. If these tests pass, then

the method seeks to determine 704 if the PREAMBLE SYSTEM CODE is in one of the several valid orthogonal groups which may be used by similar systems but which are not intended for the receiver. If the 5-10 bits subsequently received cannot be decoded 704 as a valid group, then the TRIP handler aborts to step 710. If the 5-10 bits received can be interpreted as a member of a valid group, then the algorithm acknowledges that the TRIP was not caused by jamming and clears 705 the false TRIP bit 515. Alternately, if the total message transmit time of a valid, but undesired, transmission is anticipated to last many sweeps of radio spectrum available, it may be desirable to adjust the SHUNT LEVEL accordingly, or to mark the channel as occupied or as jammed for some number of frequency sweeps.

If the PREAMBLE SYSTEM CODE matches 706 the instant receiver's preset code, then control is passed to establish 707 the data clock sample position. If the code does not match, then the algorithm passes control to A 621 so that the receiver can continue to search for possible desired signals. Steps 702, 703, 704, 706, and 707 can be combined into one hardware/software block by use of parallel correlation, table look-up or equivalent algorithmic means.

Once the data clock is established 707 then the algorithm may decode the first leading bits in the data message which may optionally contain the full system code. If the full system code does not match 708, then the transmission is not intended for the receiver and control is passed to A 621 with delay. If the full system code does match 708, then the remainder of the 1. message is decoded 709 and is used according to the application of the system. Control is then turned to A 621 in order to search for further valid signals. In addition, the transmitter's ID may be located in the leading portion of the following data. The receiver can, in conjunction, maintain a data base of 'desired' transmitter IDs which are a subset of all possible IDs. If the new message does not match the 'desired' list, then the receiver may abort the message to prevent wasted dwell time.

In the case where the TRIP handler aborted, the method determines 710 if the false TRIP is a product of frequency hoppers or other rapid pulse jammers, which are not likely to affect the next subsequent signal reading of that frequency bin. If the false TRIP bit 515 was not set 710 in the last reading of that frequency bin, then control is passed to step 712. If the last reading of that frequency bin did 710 result in a false TRIP,

then it is desirable to set 711 the SHUNT LEVEL 501 to the new jamming level. As an alternative to this approach, or to augment this approach, the attack variable 502 may be used to establish a first or second order derivative which seeks to predict the rate of rise of a rapidly increasing
5 interfering signal level.

The method sets 712 the false TRIP bit 515 in the shunt table increments 713 the false TRIP count 507 and exits the TRIP handler, returning to A 621 to seek further desired messages.

10 The method shown in FIG. 7B is used if the AGC loop seeks to use the entire dynamic range of the system. The signal level cues, which are lower than the zero level of the servo loop, cannot be used to reestablish or reduce the SHUNT LEVEL 501. Alternatively, this time-based SHUNT LEVEL decay algorithm can be used to enhance or augment the other algorithms. The time-based SHUNT LEVEL decay algorithm runs in a
15 continuous loop beginning with the step of delaying 714 for some appropriate period of time which can be in the range of a portion of a single frequency sweep or as long as many minutes. This method requires a separate shunt table pointer to be incremented 715 in order to index through the list of SHUNT LEVELS 501. An optional step may be used in
20 conjunction with a higher order loop to calculate 716 a decay. A function controlled by the decay variable 503 sets the amount W by which, in the subsequent steps, the SHUNT LEVEL 501 shall be decremented 717. The method resets 718 the shunt table pointer if the shunt table pointer has reached the end of the shunt table. The method then loops back to 714
25 and repeats.

As an alternative to these Van Newman algorithms, the prediction can be implemented by fuzzy logic or neural network means. The present signal strength or quieting reading in any frequency bin can be input, as well as other cues, to re-train the network and to yield results which
30 adapt to the radio environment, background noise, jamming and interference.

It will be apparent to those skilled in the art that various modifications can be made to the frequency agile spread spectrum system of the instant invention without departing from the scope or
35 spirit of the invention, and it is intended that the present invention cover modifications and variations of the frequency agile spread spectrum system provided they come within the scope of the

appended claims and their equivalents.

I CLAIM:

1. A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on a plurality of pseudo-random frequencies,
5 comprising the steps of:

scanning an available radio spectrum;

measuring, in a portion of the available radio spectrum, at least one of signal strength and quieting and signal lock quality, as a measurement,
10 from an output of said frequency-agile receiver;

identifying the portion of the available radio spectrum failing to provide a properly coded reception;

generating, using the measurement and other system cues, a prediction of a level of undesired signal energy, within the portion of the available radio spectrum, present in a future scan of said frequency-agile receiver; and
15

storing the prediction of the level of undesired signal energy in a memory location associated with the portion of the available radio spectrum.

2. A method, using a frequency-agile receiver in a frequency-agile-radio system, for receiving signals from a transmitter transmitting information messages on a plurality of frequencies, comprising the steps of:
20

scanning an available radio spectrum;

measuring, in a portion of the available radio spectrum, at least one of signal strength and quieting and signal lock quality, as a measurement, from an output of said frequency-agile receiver;
25

generating, using the measurement, a prediction of a level of undesired signal energy, within the portion of the available radio spectrum, present in a future scan of the frequency-agile receiver;

storing the prediction of the level of undesired signal energy in a memory location associated with the portion of the available radio spectrum; and
30

avoiding, responsive to the stored prediction, future undesired signal energy.

3. A method, using a frequency-agile receiver in a frequency-agile-radio system, for receiving signals from a transmitter transmitting information messages on a plurality of frequencies, comprising the steps of:

5 scanning an available radio spectrum;

measuring, in a portion of the available radio spectrum, at least one of signal strength and quieting and signal lock quality, as a measurement, from an output of said frequency-agile receiver;

10 identifying the portion of the available radio spectrum failing to provide a properly coded reception;

generating a prediction, using the measurement and information derived from previous measurements, of a level of undesired signal energy, within the portion of the available radio spectrum, present in a future scan of said frequency agile receiver; and

15 storing the prediction in a memory location associated with the portion of the available radio spectrum.

4. A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on a plurality of frequencies, comprising the steps of:

20 scanning an available radio spectrum;

measuring, in a portion of the available radio spectrum, at least one of signal strength and quieting and signal lock quality, as a measurement, from an output of said frequency-agile receiver;

25 comparing the measurement to a threshold stored in a memory location associated with the portion of the available radio spectrum;

ceasing, responsive to the measurement exceeding the threshold, to scan the available radio spectrum; and decoding at least one of a PREAMBLE SYSTEM CODE and a transmitter identifier.

5. The method as set forth in claim 29 wherein the step of
30 comparing the measurement to the threshold includes the step of comparing the measurement to at least one of a SHUNT LEVEL and a SHUNT LEVEL plus a TRIP LEVEL.

6. A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting

information messages on a plurality of frequencies, comprising the steps of:

scanning an available radio spectrum;

measuring, in a portion of the available radio spectrum, at least one of signal strength and quieting and signal lock quality, as a measurement,

5 from an output of said frequency-agile receiver;

comparing the measurement to a prediction stored in a memory location associated with the portion of the available radio spectrum;

ceasing, responsive to the measurement exceeding at least one of the prediction and the prediction plus a TRIP LEVEL, to scan the available radio spectrum and attempting to decode at least one of a PREAMBLE
10 SYSTEM CODE and a transmitter identifier;

continuing, responsive to the measurement not exceeding at least one of the prediction and the prediction plus a TRIP LEVEL, to scan the available radio spectrum;

15 identifying the portion of the available radio spectrum failing to provide a properly coded reception;

generating, using at least one of the measurement and other system cues, a prediction of a level of undesired signal energy, within the portion of the available radio spectrum, present in a future scan of said frequency-agile receiver; and
20

updating the prediction in a memory location associated with the portion of the available radio spectrum.

7. A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on an imperfectly known frequency, comprising the steps of:

scanning an available radio spectrum;

measuring, in a portion of the available radio spectrum, at least one of signal strength and quieting and signal lock quality, as a measurement, from an output of said frequency-agile receiver;

30 generating, using the measurement, a prediction of a level of undesired signal energy, within the portion of the available radio spectrum, present in a future scan of said frequency-agile receiver;

storing the prediction in a memory location associated with the portion of the available radio spectrum;

35 avoiding, responsive to the stored prediction, future undesired signal

energy; and

attempting to decode at least one of a PREAMBLE SYSTEM CODE and voice and data and a transmitter identifier.

5 8. A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on a plurality of frequencies, comprising the steps of:
scanning an available radio spectrum;
measuring, in a portion of the available radio
10 spectrum, at least one of signal strength and quieting and signal lock quality, as a measurement, from an output of said frequency-agile receiver;
generating, using at least one of the measurement and other system cues, a prediction of a level of undesired signal energy, within the portion of the available radio spectrum, present in a future scan of said
15 frequency-agile receiver, the prediction, responsive to an average level of undesired signal energy remaining constant, including at least one of an average prediction and an average signal SHUNT LEVEL; and
storing the prediction in a memory location associated with the portion of the available radio spectrum.

20 9. A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on a plurality of frequencies, comprising the steps of:
scanning an available radio spectrum,
measuring, in a portion of the available radio spectrum, at least one
of signal strength and quieting and signal lock quality, as a measurement,
25 from an output of said frequency-agile receiver;
generating, using at least one of the measurement and other system cues, a prediction of a level of undesired signal energy, within the portion of the available radio spectrum, present in a future scan of said
frequency-agile receiver, the prediction, responsive to at least one of
30 significant variation and rapid variation in the level of undesired signal energy, including at least one of a prediction and a SHUNT LEVEL which rapidly matches the level of undesired signal energy; and
storing the prediction in a memory location associated with the portion of the available radio spectrum.

10. A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on a plurality of frequencies, comprising the steps of:

scanning an available radio spectrum;

5 measuring, in a portion of the available radio spectrum, at least one of signal strength and quieting and signal lock quality, as a measurement, from an output of said frequency-agile receiver;

generating, using at least one of the measurement and other system cues, a prediction of a level of undesired signal energy, within the portion
10 of the available radio spectrum, present in a future scan of said frequency-agile receiver, the prediction, responsive to the measurement falling within a specified hysteresis range, including an average of past readings from the portion of the available radio spectrum; and

storing the prediction in a memory location associated with the
15 portion of the available radio spectrum.

11. A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on a plurality of frequencies, comprising the steps of:

scanning an available radio spectrum,

20 measuring, in a portion of the available radio spectrum, at least one of signal strength and quieting and signal lock quality, as a measurement, from an output of said frequency-agile receiver;

generating, using at least one of the measurement and other system cues, a prediction of a level of undesired signal energy, within the portion
25 of the available radio spectrum, present in a future scan of said frequency-agile receiver, the prediction, responsive to the measurement falling outside a specified hysteresis range, including a value equal to the present measurement; and

storing the prediction in a memory location associated with the
30 portion of the available radio spectrum.

12. A frequency error-compensation method comprising the steps of:

generating an initial known frequency harmonic as a reference within a receiver's tunable radio spectrum,

35 frequency scanning within the receiver's tunable radio spectrum;

locating the initial frequency harmonic reference; and
associating, responsive to locating the initial frequency harmonic reference, the point within the receiver's tunable radio spectrum so located, with the known frequency harmonic reference.

- 5 13. A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on a plurality of frequencies, comprising the steps of:
scanning an available radio spectrum,
measuring, in a portion of the available radio spectrum, at least one
10 of signal strength and quieting and signal lock quality, as a measurement, from an output of said frequency-agile receiver;
comparing the measurement to a threshold stored in a memory location associated with the portion of the available radio spectrum, the threshold including at least one of a SHUNT LEVEL and a SHUNT LEVEL
15 plus an adaptive TRIP LEVEL;
ceasing, responsive to the measurement exceeding the threshold, to scan the available radio spectrum; and
attempting to decode at least one of a PREAMBLE SYSTEM CODE, a transmitter identifier, voice, and data.

- 20 14. A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on a plurality of frequencies, comprising the steps of:
selecting a chirp filter while scanning an available radio spectrum;
receiving a signal;
25 measuring at least one of signal strength and quieting and signal lock quality as a measurement;
ceasing, responsive to the measurement exceeding at least one of a SHUNT LEVEL and a SHUNT LEVEL plus a TRIP LEVEL, to scan the available radio spectrum;
30 selecting at least one of an intermediate frequency (IF) filter and a baseband filter having a bandwidth similar to a bandwidth of the received signal; and
attempting to decode at least one of data and voice and a PREAMBLE SYSTEM CODE and a transmitter identifier.

15. A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on a plurality of frequencies, comprising the steps of:

scanning an available radio spectrum; receiving a signal having
5 transmitted data;

selecting a filter with a bandwidth greater than that of the transmitted data;

measuring at least one of signal strength and quieting and signal lock quality as a measurement;

10 ceasing, responsive to the measurement exceeding at least one of a SHUNT LEVEL and a SHUNT LEVEL plus a TRIP LEVEL, to scan the available radio spectrum;

selecting at least one of an IF filter and a baseband filter having a bandwidth similar to a bandwidth of the transmitted data; and

15 decoding at least one of data and voice and a PREAMBLE SYSTEM CODE and a transmitter identifier.

16. A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on a plurality of frequencies, comprising the steps of:

20 generating a local oscillator frequency by processor means;

selecting a next frequency to be received and commanding frequency generation means to an appropriate output;

reading a SHUNT LEVEL associated with the next frequency from a table stored in memory means;

25 outputting at least one of the SHUNT LEVEL and a portion of the SHUNT LEVEL to an automatic gain control (AGC) circuit;

measuring at least one of signal strength and quieting and signal lock quality, as a measurement, at an output of said frequency-agile receiver;

30 comparing the measurement to a threshold; and

decoding, responsive to the measurement exceeding the threshold, at least one of a PREAMBLE SYSTEM CODE and voice and data and a transmitter identifier.

17. The method as set forth in claim 41 wherein the step of
35 comparing the threshold includes the step of comparing the threshold to at

least one of a TRIP LEVEL, and a SHUNT LEVEL less the portion of the SHUNT LEVEL output to the AGC circuit, and a SHUNT LEVEL plus a TRIP LEVEL less the portion of the SHUNT LEVEL output to the AGC circuit.

18. A method, using a frequency-agile receiver in a
5 frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on a plurality of frequencies, comprising the steps of:
- scanning an available radio spectrum,
 - reading a SHUNT LEVEL associated with a portion of the available
10 radio spectrum from a table stored in memory means;
 - outputting at least one of the SHUNT LEVEL and a portion of the SHUNT LEVEL to an automatic gain control (AGC) circuit;
 - measuring at least one of signal strength and quieting and signal lock quality, as a measurement, at an output of said frequency-agile
15 receiver;
 - comparing the measurement to at least one of a TRIP LEVEL, a SHUNT LEVEL less the portion of the SHUNT LEVEL output to the AGC circuit, and a SHUNT LEVEL plus a TRIP LEVEL less the portion of the SHUNT LEVEL output to the AGC circuit; and
20 decoding, responsive to the measurement exceeding the at least one of a TRIP LEVEL, a SHUNT LEVEL less the portion of the SHUNT LEVEL output to the AGC circuit, and a SHUNT LEVEL plus a TRIP LEVEL less the portion of the SHUNT LEVEL output to the AGC circuit, at least one of a PREAMBLE SYSTEM CODE and voice and data and a transmitter identifier.

- 25 19. A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on an imperfectly known frequency, comprising the steps of:
- scanning an available radio spectrum;
 - 30 reading a SHUNT LEVEL associated with a portion of the available radio spectrum from a table stored in memory means;
 - outputting at least one of the SHUNT LEVEL and a portion of the SHUNT LEVEL to an automatic gain control (AGC) circuit;
 - measuring at least one of signal strength and quieting and signal
35 lock quality, as a measurement, at an output of said frequency-agile

receiver;

comparing the measurement to at least one of a TRIP LEVEL, a SHUNT LEVEL less the portion of the SHUNT LEVEL output to the AGC circuit, and a SHUNT LEVEL plus a TRIP LEVEL less the portion of the SHUNT LEVEL output to the AGC circuit; and decoding, responsive to the measurement exceeding the portion of the SHUNT LEVEL output to the AGC circuit; and

decoding, responsive to the measurement exceeding the at least one of a TRIP LEVEL, a SHUNT LEVEL less the portion of the SHUNT LEVEL output to the AGC circuit, and a SHUNT LEVEL plus a TRIP LEVEL less the portion of the SHUNT LEVEL output to the AGC circuit, at least one of a PREAMBLE SYSTEM CODE and voice and data and a transmitter identifier.

20. A method, using a frequency-agile receiver in a frequency-agile radio system, for receiving signals from a transmitter transmitting information messages on a plurality of frequencies, comprising the steps of:

generating a local oscillator frequency by processor means;
selecting a next frequency to be received and commanding frequency generation means to an appropriate output;

reading a SHUNT LEVEL associated with the next frequency from a table stored in memory means;

disabling, responsive to the SHUNT LEVEL exceeding a level equal to an attenuation caused by disabling said frequency-agile receiver's gain stage plus a required carrier-to-noise ratio to achieve a desired bit error rate (BER), said frequency-agile receiver's gain stage;

measuring at least one of signal strength and quieting and signal lock quality, as a measurement, at an output of said frequency-agile receiver;

comparing the measurement to at least one of a SHUNT LEVEL less the attenuation, and a SHUNT LEVEL plus the TRIP LEVEL less the attenuation; and

decoding, responsive to the measurement exceeding at least one of a SHUNT LEVEL less the attenuation, and a SHUNT LEVEL plus the TRIP LEVEL less the attenuation, at least one of PREAMBLE SYSTEM CODE and voice and data and a transmitter identifier.

21. The method as set forth in claim 1, 2, 3, 4, 6, 8, 13, 14, 16, 18,

or 20, further including the steps of:

receiving a transmission from a transceiver system;
associating, by a receiver portion of a transceiver,
portions of a bandwidth with levels of undesired signal energy;

5 storing information on the levels of undesired signal
energy in memory means;

transmitting, by a transmitter portion of the transceiver, data
representing the information to a remotely located transceiving device; and

10 transmitting, by the remotely located transceiving device and
responsive to the information, frequencies least associated with high levels
of undesired signal energy.

22. The method as set forth in claim 4, 6, 13, 14, 15, 16, 18, or 20,
further including the steps of:

15 accepting a PREAMBLE SYSTEM CODE as matching that of said
frequency-agile receiver; and

representing the information to a remotely located transceiving
device; and

20 transmitting, by the remotely located transceiving device and
responsive to the information, frequencies least associated with high levels
of undesired signal energy.

23. The method as set forth in claim 4, 6, 13, 14, 15, 16 or 20
further including the steps of:

comparing successive remaining repetitions of a PREAMBLE
SYSTEM CODE to continue verifying a correct match; and

25 verifying that a full system code matches a code of said
frequency-agile receiver.

24. The method as set forth in claims 4, 6, 13, 14, 15, 16 or 20
further including the steps of:

30 comparing successive remaining repetitions of a PREAMBLE
SYSTEM CODE to continue verifying a correct match; and

verifying that a transmitted ID code matches a sub- group of
desired transmitter IDs.

25. The method as set forth in claims 1, 2, 3, 4, 6, 7, 8, 13, 14, 15,

16, 18, 19, or 20, further including the steps of:

dwelling, by said frequency-agile receiver, on a portion of an available radio spectrum; and

5 aborting false dwells by verifying at least one of a modulation form, data encoding, and data sequence.

26. The method as set forth in claims 1, 2, 3, 4, 6, 7, 8, 13, 14, 15, 16, 18, 19, or 20, further including the steps of:

10 adaptively computing a TRIP LEVEL by using at least one of percent message throughput, attack variables, decay variables, and false TRIP historic information; and

dwelling, responsive to future measurements exceeding at least one of an adaptive TRIP LEVEL and an adaptive TRIP LEVEL plus a SHUNT LEVEL, on a portion of the available radio spectrum.

15 27. The method as set forth in claims 1, 3, 4, 7, 8, 13, 14, 15, 16, 18, 19, or 20, further including the steps of:

identifying a portion of the available radio spectrum as occupied;
marking the portion Of the available radio spectrum as occupied; and
avoiding, responsive to the portion of the radio spectrum being marked as occupied, the portion of the radio spectrum.

20 28. The method as set forth in claim 27 wherein the step of identifying utilizes at least one of percent data throughput, SHUNT LEVEL, attack variables, and decay variables.

25 29. The method as set forth in claim 27 wherein the step of avoiding the occupied portion of the radio spectrum includes the step of avoiding the occupied portion of the radio spectrum by at least one of skipping over and blanking and sweeping more rapidly and dumping the most narrow IF filter and dumping the baseband filter.

30 30. The method as set forth in claim 1, 2, 3, 4, 6, 7, 8, 13, 14, 15, 16, 18, 19, or 20, further including the steps of:

dwelling, by said frequency-agile receiver, on a portion of the available radio spectrum; and

controlling, responsive to at least one of an initial frequency error and a frequency drift error, at least one of a voltage controlled oscillator, a numerically controlled oscillator, a frequency synthesizer, and a reference frequency to minimize
5 frequency error.

31. The method as set forth in claim 1, 2, 3, 4, 6, 7, 8, 13, 14, 15, 16, 18, 19, or 20, further including the steps of:

10 receiving a transmission from a transmitter system which locks a carrier to a data clock;

dwelling, by said frequency-agile receiver, on a portion of the available radio spectrum; and

controlling, responsive to at least one of an initial carrier frequency error and a carrier frequency drift error, a
15 system reference frequency for canceling carrier frequency drift and data clock drift.

32. The method as set forth in claim 1, 2, 3, 4, 6, 7, 13, 14, 15, 16, 18, 19, or 20, wherein the step of generating the prediction, responsive to a level of undesired signal energy remaining constant, includes the step of
20 generating the prediction equal to an average level of undesired signal energy.

33. The method as set forth in claim 1, 2, 3, 4, 6, 7, 13, 14, 15, 16, 18, 19, or 20, wherein the step of generating the prediction, responsive to at least one of significant variation and rapid variation in the level of
25 undesired signal energy, includes the step of generating the prediction equal to an average level of undesired signal energy which rapidly matches the level of undesired signal energy.

34. The method as set forth in claim 1, 2, 3, 4, 6, 7, 13, 14, 15, 16, 18, 19, or 20, wherein the step of generating the prediction, equal to the
30 measurement falling within a specified hysteresis range, includes the step of generating the prediction equal to an average of past readings from the portion of the available radio spectrum.

35. The method as set forth in claim 1, 2, 3, 4, 6, 7, 13, 14, 15, 16, 18, 19, or 20, wherein the step of generating the prediction, responsive to the measurement falling outside a specified hysteresis range, includes the step of generating the prediction at least one of equal to and rapidly becoming equal to the present measurement.

36. The method as set forth in claim 1, 2, 3, 6, 7, 8, 13, 14, 15, 16, 18, 19, or 20, wherein the step of generating the prediction responsive to the measurement, includes the step of generating the prediction resulting from attack and decay variables based on previous measurements forming a higher order servo loop.

37. The method as set forth in claim 1, 2, 3, 6, 7, 8, 13, 14, 15, 16, 18, 19, or 20, further comprising the step of updating at least one of the prediction and the SHUNT LEVEL, predicated upon more than one false TRIP caused by at least one of a same frequency bin, and a same portion of the available radio spectrum occurring in consecutive scans of a radio spectrum.

38. The method as set forth in claim 1, 2, 3, 4, 6, 7, 8, 13, 14, 15, 16, 18, 19, or 20, wherein the step of scanning includes the steps of:
generating a next local oscillator frequency by frequency generation means;
dumping at least one of a most narrow IF filter and a baseband filter;
delaying an appropriate amount of time; and
measuring at least one of signal strength and quieting and signal lock quality.

39. The method as set forth in claim 1, 2, 3, 4, 6, 7, 8, 13, 16, 18, 19, or 20, further including the steps of:
selecting at least one of a chirp filter and a filter which has a bandwidth greater than that of transmitted data, while scanning an available radio spectrum;
measuring at least one of signal strength and quieting and signal lock quality as a measurement;
ceasing, responsive to the measurement exceeding a threshold, to

scan the available radio spectrum;

selecting at least one of an IF filter and a baseband filter having a bandwidth similar to a bandwidth of the transmitted data; and

attempting to decode at least one of data and voice and a PREAMBLE
5 SYSTEM CODE and a transmitter identifier and voice and data.

40. The method set forth in claim 38 wherein the step of dumping at least one of the most narrow IF filter and the baseband filter achieves a sharp leading edge in a frequency swept application while causing minimal peak signal attenuation.

10 41. The method as set forth in claim 1, 2, 3, 4, 6, 7, 8, 13, 14, 15, 16, 18, 19, or 20, further including the of:

delaying a period of time;

calculating a reduction factor based upon a decay algorithm;

15 subtracting the calculated reduction factor from a SHUNT LEVEL to yield a new SHUNT LEVEL; and

storing the new SHUNT LEVEL in memory means.

42. The method as set forth in claim 13, 14, 15, 16, 18, 19, or 20, further including the steps of:

20 generating, using a present measurement and historical information derived from past measurements, a prediction of a level of undesired signal energy, within a portion of the available radio spectrum, present in a future scan of said frequency-agile receiver; and

updating the prediction in a memory location associated with the portion of the available radio spectrum.

25 43. The method as set forth in claim 1, 2, 3, 4, 6, 7, 13, 14, or 15, further including the steps of:

outputting at least one of a SHUNT LEVEL and a portion of a SHUNT LEVEL to an AGC circuit;

30 measuring at least one of signal strength and quieting and signal lock quality, as a measurement, at an output of said frequency-agile receiver; and

comparing the measurement to at least one of a TRIP LEVEL, a SHUNT LEVEL less the portion of the SHUNT LEVEL output to the AGC circuit, and

a SHUNT LEVEL plus a TRIP LEVEL less the portion of the SHUNT LEVEL output to the AGO circuit.

44. The method as set forth in claim 1, 2, 3, 4, 6, 7, 13, 14, or 15, further including the step of:

5 disabling, responsive to at least one of a prediction of undesired
signal energy and a SHUNT LEVEL exceeding an amount equal to an
attenuation caused by disabling at least one of said frequency-agile
receiver's gain stages plus a carrier to noise ratio required to achieve a
desired bit error rate, at least one said frequency-agile of the receiver's
10 gain stages.

5 44. A radio transmission and reception system tolerant of frequency offset errors and capable of a high degree of sensitivity and interference rejection, comprising:
a transmitter with a tuned oscillator transmitting on an imprecisely known frequency, said transmitter including transmitter identification information generation means; and
10 a receiver having examining means to examine a portion of the radio spectrum at least equal to range of frequencies generated by the oscillator of the said transmitter; and
desired signal detection means coupled to at least one of said examining means and new signal presence detector, to determine if the transmission is from a desired
15 transmitter by examining the said identification information; and
decoding the desired transmitter signal;
whereby the examining means and detecting means achieve a degree of sensitivity greater than that possible in an un-subdivided bandwidth which is wide enough to examine the range of frequencies generated by the oscillator of the said transmitter.

20 45. The radio transmission and reception system of Claim 44, wherein there is further provided:
new signal presence detection means coupled to said examining means to pre-determine if a signal in a sub-portion of the examined radio bandwidth may be a potentially desirable signal.

25 46. The radio transmission and reception system of Claim 44, wherein:
said tuned oscillator is frequency compensated by a frequency divider and a frequency reference.

30 47. The radio transmission and reception system of Claim 50, wherein said oscillator is tuned with a crystal.

48. The radio transmission and reception system of Claims 44 and 45, wherein said means to examine a portion of the radio spectrum further includes signal processor

5 capable of implementing a multiplicity of adjacent filters, whereby each filter has a bandwidth smaller than the range of frequencies which may be generated by the said transmitter.

49. The radio transmission and reception system of Claim 48, wherein said means to examine a portion of the radio spectrum includes:

10 a signal processor which embodies means to compute a Fourier transform on at least a portion of the frequencies which may be generated by said transmitter.

50. The radio transmission and reception system of Claims 44 and 45, wherein said means to examine a portion of the radio spectrum includes:

15 a signal processor means capable of evaluating a multiplicity of independent frequencies, whereby the evaluating means has a bandwidth less than that which may be generated by the tuned oscillator of said transmitter.

51. A method, using a transmitter transmitting on an imprecisely known carrier frequency in combination with a frequency-agile radio receiver system for resolving the frequency uncertainty and to receive message-data, the message-data including at least one of message signals, voice signals, and data signals, the method comprising the steps of:

20 generating a single carrier frequency for use by said transmitter;
generating a preamble-data signal on the single carrier frequency;
transmitting the preamble-data signal for a pre-set preamble time for allowing an
25 appropriate frequency-agile receiver to lock-on the preamble-data signal; and
modulating a carrier signal having the single carrier frequency with the message-data to produce a modulated signal.
modulating the preamble-data signal with a data code, the data code including a
short identifying code;
30 repetitively sending the short identifying code on the single carrier frequency;
demodulating a portion of the data code by an associated frequency-agile receiver;
determining whether the portion of the data code is intended for the associated

- 5 frequency-agile receiver; and
discarding data codes which do not match a data code intended for the associated
frequency-agile receiver to reduce a dwell time on the carrier frequency.

52. The radio transmission and reception system of Claims 44, 45 and 51, wherein
said transmitter includes means to re-transmit an information message redundantly on a
10 multiplicity of frequencies.

53. The radio transmission and reception system of Claims 51 and 52, wherein
said redundant transmissions are separated by a pseudorandom time interval.

54. The radio transmission and reception system of Claims 44, 45 and 51, wherein
said transmitter includes means to re-transmit a message on a multiplicity of frequencies
15 and whereby each frequency, or an aggregate of the multiplicity of re-transmitted
frequencies, are separated by a bandwidth at least as great as the frequency coherence
bandwidth of the radio channel in order to minimize the effects of signal fading.




FIG. 1




FIG. 2B

FIG. 2A




FIG. 4A




FIG. 4B




FIG. 4C

2/3

FIGURE 5




FIGURE 6




FIGURE 7A





FIGURE 7B



A. CLASSIFICATION OF SUBJECT MATTER

IPC(6) : HO4B 1/713; HO4J 13/06

US CL : 375/202; 455/259

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

U.S. : 375/202, 346, 368; 455/259, 166.1, 296; 342/17, 18, 19;

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A, P	US, A, 5,452,319 (COOK ET AL) 19 SEPTEMBER 1995, col. 7, l. 59 thru col. 8, l. 36.	1-11 and 13-44.
A, P	US, A, 5,394,433 (BANTZ ET AL) 28 FEBRUARY 1995, col. 8, l. 52 thru col. 9, l. 39.	1-11 and 13-44.
X, P	US, A, 5,377,221 (MUNDAY ET AL) 27 DECEMBER 1994, col. 5, l. 28 thru col. 6, l. 64.	1-1 and 13-44.
X, P	US, A, 5,353,311 (HIRATA ET AL) 04 OCTOBER 1994, col. 2, li. 56 thru col. 3, l. 2.	12
A	US, A, 5,235,613 (BROWN ET AL) 10 AUGUST 1993, col. 2, lines 5-28.	1-11 and 13-44.
A	US, A, 5,210,771 (SCHAEFFER ET AL) 11 MAY 1993, col. 6, lines 2-58.	1-11 and 13-44.

☒ Further documents are listed in the continuation of Box C.
 ☐ See patent family annex.

* Special categories of cited documents:	T	later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
* A* document defining the general state of the art which is not considered to be of particular relevance	X*	document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
* E* earlier document published on or after the international filing date	Y*	document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
* L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)	A*	document member of the same patent family
* O* document referring to an oral disclosure, use, exhibition or other means		
* P* document published prior to the international filing date but later than the priority date claimed		

Date of the actual completion of the international search

19 JANUARY 1996

Date of mailing of the international search report

15 FEB 1996

 Name and mailing address of the ISA/US
 Commissioner of Patents and Trademarks
 Box PCT
 Washington, D.C. 20231

Facsimile No. (703) 305-3230

Authorized officer

GILBERTO BARRÓN JR.

Telephone No. (703) 306-4177

INTERNATIONAL SEARCH REPORT

International application No.
PCT/US95/12150

C (Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US, A, 4,935,940 (REINDL) 19 JUNE 1990, col. 5, lines 3-22.	1-11 and 13-44.
X	US, A, 4,752,939 (AMOROSO ET AL) 21 JUNE 1988, col. 3, lines 9-37.	44-54.
X	US, A, 4,691,377 (YOSHIHARA ET AL) 01 SEPTEMBER 1987, col. 5, l. 42 thru col. 6, l.17.	12.
A	US, A, 4,388,723 (KEEN) 14 JUNE 1983, col. 4, l. 58 thru col. 5, l. 44.	44-54.
X	US, A, 3,913, 029 (CASPARI ET AL) 14 OCTOBER 1975, col. 2, l. 51 thru col. 3, l. 15.	12.

Box I Observations where certain claims were found unsearchable (Continuation of item 1 of first sheet)

This international report has not been established in respect of certain claims under Article 17(2)(a) for the following reasons:

1. ☐ Claims Nos.:
because they relate to subject matter not required to be searched by this Authority, namely:

2. ☐ Claims Nos.:
because they relate to parts of the international application that do not comply with the prescribed requirements to such an extent that no meaningful international search can be carried out, specifically:

3. ☐ Claims Nos.:
because they are dependent claims and are not drafted in accordance with the second and third sentences of Rule 6.4(a).

Box II Observations where unity of invention is lacking (Continuation of item 2 of first sheet)

This International Searching Authority found multiple inventions in this international application, as follows:

Please See Extra Sheet.

1. ☒ As all required additional search fees were timely paid by the applicant, this international search report covers all searchable claims.
2. ☐ As all searchable claims could be searched without effort justifying an additional fee, this Authority did not invite payment of any additional fee.
3. ☐ As only some of the required additional search fees were timely paid by the applicant, this international search report covers only those claims for which fees were paid, specifically claims Nos.:

4. ☐ No required additional search fees were timely paid by the applicant. Consequently, this international search report is restricted to the invention first mentioned in the claims; it is covered by claims Nos.:

Remark on Protest

- ☐ The additional search fees were accompanied by the applicant's protest.
☐ No protest accompanied the payment of additional search fees.

BOX II. OBSERVATIONS WHERE UNITY OF INVENTION WAS LACKING

This ISA found multiple inventions as follows:

This application contains the following inventions or groups of inventions which are not so linked as to form a single inventive concept under PCT Rule 13.1. In order for all inventions to be examined, the appropriate additional examination fees must be paid.

Group I, claim(s) 1-11 and 13-44, drawn to method of using a frequency agile receiver.

Group II, claim(s) 12, drawn to method for frequency error compensation.

Group III, claim(s) 44-54, drawn to transmission and reception system tolerant of frequency offset error. The inventions listed as Groups I, II and III do not relate to a single inventive concept under PCT Rule 13.1 because, under PCT Rule 13.2, they lack the same or corresponding special technical features for the following reasons: Group II provides for the special technical feature of frequency error compensation using harmonic reference comparison not required by Groups I and III. Group III provides for the special technical feature of detection of identification information not required by Groups I and II. Group I provides for the special technical feature of measuring levels received by a frequency agile receiver not required by Groups II and III.